

TECNOLUMEN

TECNOLUMEN GmbH & Co. KG • Lötzeener Str. 2-4 • D-28207 Bremen • Tel (0421) 430 41 70 • Fax (0421) 4986685

Assembly instructions and important information DAD 33

Technical details:

Power supply: 110-240 V / 50-60 Hz

Bulb socket: S14d

Protection class: II

Maximum wattage (thermal):

Line-bulb 2x 35 W

Recommended bulb:

LED line-lamp 6W

Safety instructions:

- This luminaire may only be wired to the mains by a qualified electrician.
Improper connection causes safety hazards!
- Always ensure that the electricity is switched off when working on the luminaire or changing the bulb.
- Have repair work performed only by an authorized electrician, because electrical power can cause severe injuries!

Care of lamp:

Use a standard commercial cleaner for the glass pane.

For cleaning the wood plate only use a damp micro fibre cloth.

Mounting the luminaire:

- Remove both enclosures of bulb.
- Lead the connecting cable provided by you through the wood plate and mark the drill-holes positions on the ceiling.
- Make the drilled holes with a 6 mm masonry drill.
- Fit the luminaire to the ceiling by using the enclosed screws and rawlplugs.
- Have the electrical connection installed by an electrician as shown in the connection diagram and affix the enclosures of bulb.
- Mount the glass pane to the luminaire (matt side up).

Connection diagram:

