

TECNOLUMEN

TECNOLUMEN GmbH & Co. KG • Lötzeener Str. 2-4 • D-28207 Bremen • Tel (0421) 430 41 70 • Fax (0421) 4986685

Assembly instructions and important information HP 28/500 HP 28/700

Technical details:

Power supply: 110-240 V / 50-60 Hz

Bulb socket: E27

Protection class: I

Maximum wattage (thermal):

Halogen 4x 60 W / 6x 60 W

Recommended bulbs:

energy-saving bulbs 23 W

Safety instructions:

- Never cover the luminaire with a cloth – fire hazard!
- This luminaire may only be wired to the mains by a qualified electrician.
Improper connection causes safety hazards!
- Always ensure that the electricity is switched off when working on the luminaire or changing the bulb.
- Have repair work performed only by an authorized electrician, because electrical power can cause severe injuries!
- Some of the lamp components may get very hot in operation! Avoid skin contact with these components to prevent burns.

Care of lamp:

Use a standard commercial cleaner for the glass plate.

Please do not use a cleaning agent to clean the painted parts — only use a damp cloth.

For the chrome plated parts use a chrome polish.

Mounting the luminaire:

- Loosen the small screw in the ceiling canopy and then hang the luminaire up on the ceiling hook which you must supply.
- Let a qualified electrician connect the luminaire to the mains in accordance with the connecting diagram. Fix the ceiling canopy above the terminals.
- To mount the glass plate, unscrew the oblong head lock nut counterclockwise and remove the retention plate. Then first hold the glass plate (**mat side up**) and then the retention plate over the threaded tube and fasten it with the head lock nut.

Connecting diagram:

